

Thiele Small Parameter Changes for Two Drivers

Single Driver T/S Parameter	Two Drivers Wired in Parallel	Two Drivers Wired in Series
f_d	f_d	f_d
Q_{ed}	Q_{ed}	Q_{ed}
Q_{md}	Q_{md}	Q_{md}
Q_{td}	Q_{td}	Q_{td}
R_e	$R_e / 2$	$2 R_e$
L_{vc}	$L_{vc} / 2$	$2 L_{vc}$
V_{ad}	$2 V_{ad}$	$2 V_{ad}$
Bl	Bl	$2 Bl$
S_d	$2 S_d$	$2 S_d$